AviaSafe

COMPLIANCE

STANAG 3316

• Rapid Exit Taxiway Indicator Light

CAP 168

TP312

APPLICATIONS

Runway Centerline

ICAO

EASA

FAA

IEC

NATO

CAA

IAAE

(RETIL)

IN-RL

LED Inset Runway Centerline & Rapid Exit Taxiway Indicator Light





Aviasafe GmbH

Factory

Frauenlob Str.8

DE 98597 Fambach Neue Wiese 2

Headoffice DE 60478 Frankfurt am Main/ Germany Tel +49 69 970 863 97



FEATURES & BENEFITS

Annex 14 - Volume I

CS-ADR-DSN

• LED Bidirectional 12"

• Average LED life of 60,000 hours at full

CS-ADR-DSN

AC150/5345-46 & EB No.67D

TS 61827

• Average LED life of 60,000 hours at furintensity but over 100,000 hours in typical operating conditions.

 Very low energy consumption compared to halogen lights, resulting in a lower range of CCRs and transformers.

• Low life cycle costs due to the long LED lifespan.

 Operates on 3-step or 5-step ferroresonant or thyristor CCRs.

 In compliance with FAA & EASA standards.

 Fully compatible with existing Airfield Lighting infrastructure. Installation on the same mounting device as most conventional lights for a straightforward replacement.

- IP68: Dust-tight and protected against submersion in water.
- Designed with few mechanical parts, resulting in a more affordable price and allowing for longer maintenance intervals.
- Fully dimmable lights. The light output is variable, similar to a traditional halogen light, operating within the 2.8 A to 6.6 A range.
- Low protrusion, Style 3 inset light fixtures.
- The electronics are fully encapsulated.
- Optimized LED performance ensures there are no visual flickers.
- The Dome is designed with no negative slope in front of the prism.
- Built-in voltage surge and lightning protection.

INSTALLATION

Light fixture can be installed in 12-inch Shallow Base & Deep Base.

Refer to the user manual DC-MN-IN-12

ENVIRONMENTAL CONDITIONS

Temperature: -45 °C to +55 °C -49 °F to +131 °F Humidity: Up to 100%

DIMENSIONS & WEIGHT

Diameter: 304 mm Depth: 106 mm Weight: 8.3 kg



IN-RL


LED Inset Runway Centerline & Rapid Exit Taxiway Indicator Light


MAIN COMPONENTS OF THE LIGHT UNIT


- 01. Dome (Upper Cover)
- 02. Prism Gasket
- 03. Prism
- 04. Prism holder gasket
- 05. Prism holder
- 06. TIR
- 07. LED PCB
- 08. Heatsink
- 09. O-Ring for dome (internal)
- 10. O-Ring for lower cover
- 11. Lower cover with electronics
- 12. Gland with accessories
- 13. Valve for watertightness test
- 14. Plug(lead wire)



PHOTOMETRIC PERFORMANCE







| ELECTRICAL TABLE | | | | |
|-------------------------------|---------------------|---------|--------------|------|
| ТҮРЕ | Consumption at 6.6A | | Power Factor | |
| | 1 Plug | 2 Plugs | 2.8A | 6.6A |
| Unidirectional Without Heater | 20 VA | - | 0.96 | 0.98 |
| Unidirectional With Heater | 60 VA | - | 0.96 | 0.98 |
| Bidirectional Without Heater | 31 AV | 40 AV | 0.96 | 0.98 |
| Bidirectional With Heater | 71 AV | 120 AV | 0.96 | 0.98 |





• C: Without Heater

3